

Latest recommended config:

\_tnx\_profile.jcf

```
"BluetoothSPP": {
  "On": true,
  "Filter": "RS5100",
  "PIN": "12345", (or "")
  "UseDeviceMajor": false,
  "UnpairAll": true,
  "DiscoveryOn": false,
  "BarcodeType": "FNC3",
  "ShowUnpairBarcode": false,
  "ScannerType": 110,
  "TerminatorWait": 0,
  "Terminators": ""
},
```

Tested successfully on:

Android Oreo (8.x)					
Manufacturer	Device	Android Version	Date	Tnx version	Recommended Config
	Notes				

Android Nougat (7.x) - <a href="#">No more tested on this version</a>					
Manufacturer	Device	Android Version	Date	Tnx version	Config deviation / Notes

Zebra	WT6000	5.1.1	31/03/20	Emulator 1.0.13.513 BT Pairing 7.0.4.505 Vxt Engine 4.2.5.502 Vxt Calibrate 6.1.2.507	<code>"Filter": "RS5100",</code> <code>"UnpairAll": true,</code> <code>"ScannerType": 110,</code>
	<ul style="list-style-type: none"> <li>• Build number 04-10-03-L-00-MV-061617</li> <li>• Scanner reconnected by getting the scanner close to the device again</li> <li>• Voice projects: <ul style="list-style-type: none"> <li>◦ vxt configuration.jcf file</li> </ul> </li> </ul> <pre> "Microphone": {   "Mode": "WIRELESS",   "AskUser": "1",   "Bluetooth": {     "Filter": "HS3100",     "PIN": "",     "UnpairAll": false,     "UseDeviceMajor": true,     "IntentScanner": {       "Action": "",       "Extra": "",       "HasCategory": false,       "Category": ""     },     "UseScanCamera": false,     "AbortSpeechWhenLost": false,     "ScoReconnectTime": 999,     "ReconnectText": "Headset reconnected",     "AudioMode": "MODE_NATIVE"   } }, </pre> <ul style="list-style-type: none"> <li>◦ Headset reconnected successfully</li> </ul>				

## Recommendations:

- Use the Filter parameter as much as you can. It will be easier to establish the connection between devices.

## Scanner Type 110:

- The use of ScannerType: 110 for Zebra devices requires the BT Pairing service at Android Accessibility menu option to be activated.
- With the scanner Zebra RS5100, it is convenient to use the Filter parameter (Filter: "RS5100") to avoid having some problems when you establish the connection between the device and the scanner.
- In addition, it is convenient to use UnpairAll: true with the Zebra devices.
- Before using the scanner, please, scan the SPP mode (Discoverable) and the Non-

AutoReconnect barcodes:



**SPP Bluetooth Classic (Discoverable)**