

In the `_tnx_profile.jcf` file, set the `Scanner.Sdk.On` and `BluetoothSPP.On` parameters to false:

```
"Scanner": {
  "Sdk": {
    "On": false,
    "Readers": [
      ...
    ],
    ...
  },
  "BluetoothSPP": {
    "On": false,
    "Filter": "",
    ...
  },
  ...
}
```

Configure scanning through Intent in the same file (`_tnx_profile.jcf`)

```
"IntentScanner": {
  "Action": "com.datawedgetotellnext.barcode",
  "Extra": "com.symbol.datawedge.data_string",
  "CodeType": "com.symbol.datawedge.label_type",
  "HasCategory": false,
  "Category": ""
}
```

Open DataWedge at the Zebra device and configure the Intent output from the default profile as follows:

- Set the Intent Action as `com.datawedgetotellnext.barcode`
- Set the delivery as a Broadcast intent



