

Manual firmware update

Connect the scanner to the PC using this barcode:



Go to Bluetooth & other devices settings on your PC to add a new bluetooth connection:

- Click on Add a device.
- Wait until the device to connect is fully discovered.
- Please be sure that the scanner device is now showed at the bluetooth settings as display.
- After the bluetooth serial pairing is done, you will not be hearing any chime up sound indicating successful connection at this time.





Open EZConfig in your PC and refresh the connected device discovery window.



Update firmware

Honeywell | Scanning & Mobility

EZConfig



EzConfig will start oppening the port communication with your scanner.

Honeywell Scanning & Mobili	ty EZConfig
	GETTING STARTED NEW FEATURES CHECK FOR EZCONFIG UPDATES FAQ HELP TECHNICAL KNOWLEDGE BASE
DISCONNECTED DEVICE	
A Home ► Connected Device	Device discovery is in progress 50%
Note: No device found.	
CONFIGURE DEVICE	UPDATE FIRMWARE SCAN DATA WINDOW
ns & Conditions Privacy Statement Contact Information Feedback About	Ver: 4.5.53 © 2022 Honeywell Inc. All rights reserved



During device discovering you will notice that the scanner will start beeping chimes up and chimes down until the communication is successfully stablished.

Once the communication is stablished, select the scanner to upgrade (to determine which scanner is already selected, look for the scanner inside a green contour) and click on "UPDATE FIRMWARE"

Honeywell Scanning & Mobil	lity	EZConfig
	GETTING STARTED NEW FEATURES CHECK FOR EZConfig UPDATES FAQ HELP TECHNI	CAL KNOWLEDGE BASE
CONNECTED DEVICE		
A Home Connected Device		
Ø Refresh		
Fing Scanner 8675iSR Wireless Area-Imaging Scanner		
Model: 8675ISR Serial No: 22226B2ED2 Firmware No: GI000087BAA Connection: UNKNOWN <u>Show License/Plug-in Info</u> Firmware is up to date		
Note: Click on the device to connect / disconnect		
CONFIGURE DEVICE	UPDATE FIRMWARE SCAN DATA WINDOW	
Terms & Conditions Privacy Statement Contact Information Feedback About	Ver: 4.5.53 © 2022 Honeywell	Inc. All rights reserved

Click on browse and select the new firmware for your device previously downloaded from the Honeywell site.

PAY ATTENTION! Download the correct firmware depending on your device (FR or SR version)



Honeywell | Scanning & Mobility

EZConfig

	GETTING STARTED) NEW FEATURES CHECK FOR EZConfig UPDATES FAQ HELP TECHNICAL KNOWLEDGE BASE
CONNECTED DEVICE		
A Home ► Connected D	evice	
Device Details	Device/Model : Ring Scanner 8675/SR Wireless Area-Imaging Scanner Serial Number : 2222682ED2 Firmware Number : GI0000878AA	Update from File File Name: Update Device
Note: To obtain the latest firmwa	are updates for your device, please contact Honeywell Tec CONFIGURE DEVICE	hnical Support NA EMEA LA APAC. or Contact 1-800-867-5309 PDATE FIRMWARE SCAN DATA WINDOW Ver. 4 5 53 @ 2022 Measured line. 48 texture researced
Terms & Conditions Privacy Statemen	it Contact Information Feedback About	Ver: 4.5.53 © 2022 Honeywell Inc. All rights reserved

Once you have selected the firmware to push, click on "Update Device" and your scanner will start being Updated.

me > Connected I	Device ► Update Fi	rmware			
Device Details			Update Wom File Prepare for upgrading	CillingerildE000291Down(Dec	120
	Device/Model	: Ring Scanner 8675ISR Wireless Area-Imaging Scanner	File Name:	C. IOSCISICIOUSSOCIOMIN DIO	Update Device
Ser Fin	Serial Number	: 2222682ED2			
	Firmware Number	: GI000087BAA			
o obtain the latest firm	ware updates for your de	vice, please contact Honeywell	Technical Support NA EM	EA LA APAC. or Contact 1-800-86	7-5309

Please do not remove the battery of the scanner neither disconnect or turn off your machine during



this process. After this, you will have successfully updated your device!

Honeywell	Scanning & Mobility	EZConfig
CONNECTED DEVICE	GETT	NG STARTED NEW FEATURES CHECK FOR EZCooling UPDATES FAQ HELP TECHNICAL KNOWLEDGE BASE
A Home > Connected	Device	
Device Details	Device/Model : Ring Scanner 8675i Wireless Area-Imag Scanner Serial Number : 2222682ED2 Firmware Number : GI000087BAA	Update from File File transfer complete, Scanner is updating firmwareame: Please do not turn off the Scanner! Update Device
Note: To obtain the latest firm	ware updates for your device, please contact He	neywell Technical Support NA EMEA LA APAC. or Contact 1-800-867-5309
erms & Conditions Privacy Statem	CONFIGURE DEVICE	UPDATE FIRMWARE SCAN DATA WINDOW Ver: 4.5.53 © 2022 Honeywell Inc. All rights reserved



Update firmware

Honeywell | Scanning & Mobility

EZConfig

	GETTING STARTED NEW FEATURES CHECK FOR EZCONING UPDATES FAQ HELP TECHNICAL KNOWLEDGE BASE
A Home ► Connected Device	
🚫 Refresh	
Pine Scanner 8476150	
Wireleas Area-Imaging Scanner	
Model: 8675iSR Serial No: 22226B2ED2 Firmware No: G1000096BAA	
Connection: UNKNOWN	
Show License/Plug-in Info	
Firmware is up to date	
Note: Click on the device to connect / disconnect	
CONFIGURE DEVIC	CE UPDATE FIRMWARE SCAN DATA WINDOW
	Var. 4 6 63 /6 2022 Monazonali Inc. All dobite razamad