

Latest recommended config:

_tnx_profile.jcf

```
"BluetoothSPP": {
  "On": true,
  "Filter": "RS6000",
  "PIN": "",
  "UseDeviceMajor": false,
  "UnpairAll": true,
  "DiscoveryOn": false,
  "BarcodeType": "FNC3",
  "ShowUnpairBarcode": false,
  "ScannerType": 110,
  "TerminatorWait": 0,
  "Terminators": ""
},
```

Tested successfully on:

Android Oreo (8.x)					
Manufacturer	Device	Android Version	Date	Tnx version	Recommended Config
	Notes				

Android Nougat (7.x) - No more tested on this version					
Manufacturer	Device	Android Version	Date	Tnx version	Config deviation / Notes

Zebra	WT6000	5.1.1	30/03/20	Emulator 1.0.13.513 BT Pairing 7.0.4.505 Vxt Engine 4.2.5.502 Vxt Calibrate 6.1.2.507	"Filter": "RS6000", "UnpairAll": true, "ScannerType": 110,
	• Build number 04-10-03-L-00-MV-061617 • Scanner reconnected by getting the scanner close to the device again • Voice projects: ◦ vxt configuration.jcf file <pre> "Microphone": { "Mode": "NFC", "AskUser": "1", "Bluetooth": { "Filter": "HS3100", "PIN": "", "UnpairAll": false, "UseDeviceMajor": true, "IntentScanner": { "Action": "", "Extra": "", "HasCategory": false, "Category": "" }, }, "UseScanCamera": false, "AbortSpeechWhenLost": false, "ScoReconnectTime": 999, "ReconnectText": "Headset reconnected", "AudioMode": "MODE_NATIVE" }, }, </pre> ◦ Headset reconnected successfully				

Recommendations:

- Use the Filter parameter as much as you can. It will be easier to establish the connection between devices.

Scanner Type 110:

- The use of ScannerType: 110 for Zebra devices requires the BT Pairing service at Android Accessibility menu option to be activated.
- In addition, it is convenient to use UnpairAll: true with the Zebra devices.
- Before using the scanner, please, scan the SPP mode (Discoverable):



SPP Bluetooth Classic (Discoverable)