

Generic configuration file: _tnx_profile.jcf

```
"Bluetooth": {
  "OnAtOpen": false,
  "OffAtClose": true,
  ...
}
...
"BluetoothSPP": {
  "On": true,
  "Filter": "",
  "PIN": "1234",
  "UseDeviceMajor": false,
  "UnpairAll": true,
  "DiscoveryOn": false,
  "BarcodeType": "HONEYWELL",
  "ShowUnpairBarcode": true,
  "ScannerType": 4,
  "TerminatorWait": 0,
  "Terminators": ""
},
```

Generic configuration file: _tnx_application.jcf

```
"Bluetooth": {
  "OnAtStart": false,
  "OffAtExit": true
}
```

Tested successfully on:

Android 8+					
Manufacturer	Device	Android Version	Date	Tnx version	Recommended Config
	Notes				
Datalogic	MEMOR10	9	10/01/21	Emulator 1.0.15.507 BT Pairing 7.0.4.512	
	Build number 2.05.07.20200813				

Android Nougat (7.x) - No more tested on this version					
Manufacturer	Device	Android Version	Date	Tnx version	Config deviation / Notes

Notes:

- Once connected the scanner will not connect to another device until you have re-scanned the "Unlink Scanner" barcode.

Configuration:

- Before first use reset configuration (PAPDFT)
- Scan "Auto Reconnect Off" (BT_ACM0)
- Scan "Clear All Suffixes" (SUFGA2)
- Scan "Unlink Scanner" (BT_RMV)



PAPDFT.

**Custom Default Settings:
All Work Groups**



BT_ACM0.

Auto Reconnect Off



SUFCA2.

Clear All Suffixes

BT_RMV.

Unlink Scanner